

داده پردازی فن آوا

راهنمای تنظیمات مودم





ابتدا یک مرورگر باز کرده و در ADDRESS BAR آی پی 192.168.1.1 را تایپ کرده و سپس دکمه ENTER را فشار دهید



بعد از چند لحظه پنجره جدیدی باز شده که از شما Username و Password مودم را درخواست می نماید این مقادیر بصورت پیش فرض admin و admin (بصورت حروف کوچک) است. آنها را وارد کرده و روی دکمه Sign in کلیک کنید

Sign in

http://192.168.1.1

Your connection to this site is not private

Username

Password



پس از ورود به مودم مراحل زیر را انجام دهید:

- ۱- بر روی Setup کلیک کنید
 - ۲- بر روی Basic Setup کلیک کنید
 - ۳- قسمت Multiplexing گزینه LLC فعال شود
 - ۴- قسمت Autodetect غیر فعال یا Disable باشد
 - ۵- قسمت Virtual Circuit مقادیر VPI و VCI متناسب با محدوده جغرافیایی باید ثبت شود. برای دریافت این مقادیر با ما تماس بگیرید
 - ۶- User Name و Password که شرکت در اختیار شما قرار داده را وارد کنید
- در مرحله آخر بر روی Save Settings کلیک کنید

LINKSYS[®] by Cisco Firmware Version: V1.00.07

Wireless-N ADSL2+ Modem Router WAG120N

Setup | Setup | Wireless | Security | Access Restrictions | Applications & Gaming | Administration | Status

Basic Setup | DDNS | MAC Address Clone | Advanced Routing

Network Setup (WAN)

Internet Connection Type

Encapsulation: RFC 2364 PPPoA

Multiplexing: LLC VC

QoS Type: UBR

PCR: cps

SCR: cps

Autodetect: Enable Disable

Virtual Circuit: VPI (Range 0-255) VCI (Range 0-65535)

DSL Modulation: MultiMode

PPPoA Settings

User Name: Password:

Connect on Demand - Max Idle Time: 5 minutes

Keep Alive - Redial Period: 30 seconds

Optional Settings (required by some ISPs)

Host Name: Domain Name: MTU: Auto Size: 1492

Network Setup (LAN)

Modem Router IP

Local IP Address: Subnet Mask: 255.255.255.0

Network Address Server Settings (DHCP)

DHCP Server: Enable Disable DHCP Relay

DHCP Relay Server IP: Starting IP Address: 0.0.0.0

Maximum Number of DHCP Users: 0

Client Lease Time: 0 minutes (0 means one day)

Static DNS 1: Static DNS 2: Static DNS 3: WINS:

Time Settings

Time Zone: (GMT) Greenwich Mean Time: Dublin, Edinburgh, Lisbon, London

Automatically adjust clock for daylight saving time

Language

English

Save Settings Cancel Changes

CISCO



جهت تنظیم وایرلس مودم:

- ۱- بر روی Wireless کلیک کنید
- ۲- بر روی Basic Wireless Settings کلیک کنید
- ۳- در قسمت Network Name (SSID) نام وایرلس خود را وارد کنید
- ۴- بر روی Save Settings کلیک کنید

The screenshot shows the Linksys by Cisco web interface. At the top, the logo 'LINKSYS by Cisco' is on the left, and 'Firmware Version: V1.00.07' is on the right. Below the logo, the router model 'Wireless-N ADSL2+ Modem Router' and 'WAG120N' are displayed. A navigation menu includes 'Setup', 'Wireless', 'Security', 'Access Restrictions', 'Applications & Gaming', 'Administration', and 'Status'. The 'Wireless' menu is expanded, showing 'Basic Wireless Settings', 'Wireless Security', 'Wireless MAC Filter', and 'Advanced Wireless Settings'. The 'Basic Wireless Settings' page is active, showing 'Wireless Configuration' with 'Manual' selected. Other settings include 'Network Mode' (Mixed), 'Network Name (SSID)' (empty), 'Radio Band' (Auto), 'Wide Channel' (9), 'Standard Channel' (11 - 2.462 GHz), and 'SSID Broadcast' (Enable). At the bottom, there are 'Save Settings' and 'Cancel Changes' buttons. Red arrows with numbers 1 through 4 point to the 'Wireless' menu, 'Basic Wireless Settings' link, the 'Network Name (SSID)' field, and the 'Save Settings' button, respectively.



جهت تنظیم امنیت وایرلس مودم:

- ۱- بر روی Wireless Security کلیک کنید .
- ۲- در قسمت Security Mode گزینه WPA2-Mixed را انتخاب کنید.
- ۳- در قسمت Pre-Shared Key رمز وایرلس مودم را وارد کنید. مقادیر باید حداقل ۸ کارکتر باشد.
بر روی Save Settings کلیک کنید

LINKSYS[®] by Cisco

Firmware Version: V1.00.07

Wireless-N ADSL2+ Modem Router WAG120N

Wireless

Setup Wireless Security Access Restrictions Applications & Gaming Administration Status

Basic Wireless Settings | **Wireless Security** | Filter | Advanced Wireless Settings

Wireless Security

Security Mode: WPA2-Mixed

Encryption: TKIP or AES

Pre-Shared Key:

Key Renewal: 3600 seconds

Save Settings Cancel Changes

Help...

CISCO