

داده پردازی فن آوا

راهنمای تنظیمات مودم

TD-W8951ND





ابتدا یک مرورگر باز کرده و در ADDRESS BAR آی پی 192.168.1.1 را تایپ کرده و سپس دکمه ENTER را فشار دهید



بعد از چند لحظه پنجره جدیدی باز شده که از شما Username و Password مودم را درخواست می نماید این مقادیر به ترتیب بصورت پیش فرض admin و admin می باشد. آنها را وارد کرده و روی دکمه Sign in کلیک کنید

Sign in

http://192.168.1.1

Your connection to this site is not private

Username

Password



پس از ورود به مودم بر روی گزینه Quick Start کلیک کنید

TP-LINK®

150Mbps Wireless N ADSL2+ Modem Router

Navigation menu: Status (selected), Quick Start, Interface Setup, Advanced Setup, Access Management, Maintenance, Status, Help

Sub-menu: Device Info (selected), System Log, Statistics

Status

Device Information

Firmware Version : 5.0.0 Build 120522 Rel.23978
MAC Address : a0:f3:c1:d0:b5:13

LAN

IP Address : 192.168.1.1
Subnet Mask : 255.255.255.0
DHCP Server : Enabled

Wireless

Current Connected Wireless Clients number is 0

ID	MAC
----	-----

WAN

بر روی گزینه RUN WIZARD کلیک کنید

TP-LINK®

150Mbps Wireless N ADSL2+ Modem Router

Navigation menu: Quick Start (selected), Quick Start, Interface Setup, Advanced Setup, Access Management, Maintenance, Status, Help

Quick Start

This ADSL Router is ideal for home networking and small business networking. The 'Quick Start' wizard will guide you to configure the ADSL router to connect to your ISP (Internet Service Provider).



بر روی NEXT کلیک کنید

TP-LINK®

Quick Start

The Wizard will guide you through these four quick steps. Begin by clicking on **NEXT**.

- Step 1. Choose your time zone
- Step 2. Set your Internet connection
- Step 3. Wireless network configuration
- Step 4. Save settings of this ADSL Router



NEXT EXIT

در این قسمت گزینه Tehran (GMT +03:30) انتخاب شود. و سپس بر روی NEXT کلیک کنید

TP-LINK®

Quick Start - Time Zone

Select the appropriate time zone for your location and click **NEXT** to continue.



(GMT+03:30) Tehran



BACK NEXT EXIT



گزینه PPPoE/PPPoA انتخاب شود. و سپس بر روی NEXT کلیک کنید

TP-LINK®

Quick Start - ISP Connection Type

Select the Internet connection type to connect to your ISP. Click **NEXT** to continue.

Dynamic IP Address

Choose this option to obtain a IP address automatically from your ISP.

Static IP Address

Choose this option to set static IP information provided to you by your ISP.

PPPoE/PPPoA

Choose this option if your ISP uses PPPoE/PPPoA. (For most DSL users)

Bridge Mode

Choose this option if your ISP uses Bridge Mode.

BACK NEXT EXIT



در این صفحه :

- ۱- User Name و Password که شرکت در اختیار شما قرار داده را وارد کنید .
- ۲- مقادیر VPI و VCI متناسب با محدوده جغرافیایی باید ثبت شود. برای دریافت این مقادیر با ما تماس بگیرید.
- ۳- قسمت Connection Type گزینه PPPoE LLC انتخاب شود.
- ۴- بر روی NEXT کلیک کنید

TP-LINK®

Quick Start - PPPoE/PPPoA

Enter the PPPoE/PPPoA information provided to you by your ISP. Click **NEXT** to continue.

① → Username:

② → Password:

③ → VPI: (0~255)

④ → VCI: (1~65535)

⑤ → Connection Type: ▼

BACK NEXT EXIT



در این صفحه :

- ۱- قسمت Access Point گزینه Activated انتخاب شود.
- ۲- در قسمت (SSID) نام وایرلس خود را وارد کنید .
- ۳- قسمت Broadcast SSID گزینه Yes انتخاب شود.
- ۴- قسمت Authentication Type گزینه Auto-WPA/WPA2 انتخاب شود.
- ۵- در قسمت Pre-Shared Key رمز وایرلس مودم را وارد کنید. مقادیر باید حداقل ۸ کاراکتر باشد.
- ۶- بر روی NEXT کلیک کنید .

TP-LINK®

Quick Start - Wlan

You may enable/disable Wlan, change the Wlan SSID and Authentication type in this page.
Click **NEXT** to continue.

① → Access Point : Activated Deactivated

SSID : ← ②

③ → Broadcast SSID : Yes No

Authentication Type : ← ④

Encryption : ↓

⑤ → Pre-Shared Key : (8~63
ASCII characters or 64 hexadecimal characters)

⑥ →



در این صفحه بر روی NEXT کلیک کنید

TP-LINK®

Quick Start Complete !!

The Setup Wizard has completed. Click on **BACK** to modify changes or mistakes. Click **NEXT** to save the current settings.



بر روی CLOSE کلیک کنید

TP-LINK®

Quick Start Completed !!

Saved Changes.

